

TurboRez GS - DLC Command format and parameters

#	Cmd	Parm 1	Parm 2	Name	Description
0	\$00	Lo Addr	Hi Addr	dSet_Source	--- Set Source address
1	\$10	Lo Addr	Hi Addr	dSet_Target	--- Set Target address (+ offset)
2	\$20	OffsetL	OffsetH	dSet_Offset	--- Set Offset value
3	\$30	Lo Data	Hi Data	dSet_Reg3	--- Set Register #3 (Word)
4	\$40	Lo Data	Hi Data	dSet_Reg4	--- Set Register #4 (Word)
5	\$50	Lo Data	Hi Data	dSet_Reg5	--- Set Register #5 (Word)
6	\$60	Lo Data	Hi Data	dSet_Reg6	--- Set Register #6 (Word)
7	\$70	Color	Repeat	dSet_Reg7	--- Set Register #7 (Word)
8	\$80	Hi Addr	Lo Addr	dJump	--- DList Jump (to Address)
9	\$90	Skip #		dLine_Skip	--- No DList for nxt (Skip#) lines
A	\$A0	Length		dBlit_1	--- Start Blit 1 seq of (Length) bytes
B	\$B0	\$B0		dNull	--- Do-nothing for 2 DList Cycles
C	\$Cn			dStop	--- Stop DList (till next HBlank)
D	\$D0			dPal_Wrt	--- Start palette write sequence
E	\$E0			dBlit_2	--- Start Blit 2 sequence
F	\$Fn			dSet_VBL	--- Begin/End VBlank time